

# LE1M35N722

TeSys LE - enclosed DOL starter - 12...16 A - 415 V  
AC coil



## Main

Range	TeSys
Product name	TeSys LE
Device short name	LE1M
Product or component type	Enclosed DOL starter
Device application	Standard
Utilisation category	AC-3
Device composition	Contacteur Neutral terminal Earth terminal Thermal overload relay
Thermal protection adjustment range	12...16 A
Motor power kW	4 kW at 240 V AC 50/60 Hz 7.5 kW at 380/400 V AC 50/60 Hz 7.5 kW at 415 V AC 50/60 Hz 3.7 kW at 220/230 V AC 50/60 Hz
[Uc] control circuit voltage	415 V AC 50/60 Hz
Control type	Push-button start green I Push-button stop/reset red O

## Complementary

Local signalling	LED yellow operating
Cable entry number	2 cable entry : Pg 13 top 2 cable entry : ISO20 top 2 cable entry : ISO20 bottom 2 cable entry : Pg 13 bottom 2 cable entry : Pg 16 bottom 2 cable entry : ISO25 top 2 cable entry : Pg 21 bottom 2 cable entry : ISO25 bottom 2 cable entry : Pg 21 top 2 cable entry : Pg 16 top
Width	78 mm
Height	160 mm
Depth	108 mm
Product weight	0.6 kg

## Environment

material	ABS (acrylonitrile butadiene-styrene)
IP degree of protection	IP65 conforming to IEC 60529
standards	IEC 60947-4-1
ambient air temperature for operation	-5...40 °C
environmental characteristic	Standard environment

## Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 0718 - Schneider Electric declaration of conformity
REACH	Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Available

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

