



Main

Device short name	OF SD SDE SDV
Product or component type	Auxiliary contact
Range compatibility	Compact Compact NS1600b...3200 Compact Compact NS630b...1600 Compact Compact NSX Compact Compact NG Compact Compact NR Easypact EasyPact CVS Compact Compact INS Compact Compact INSE Compact Compact INSJ Compact Compact INV
Offer type	C4 C5
Signal contacts composition	1 NO/NC

Complementary

Auxiliary contacts type	Low level
Auxiliary contacts operation	Early-break Early-make
[I _{th}] conventional free air thermal current	5 A
[I _e] rated operational current	Utilisation category DC-12 : 0.3 A network: DC at 250 V Utilisation category DC-12 : 0.6 A network: DC at 110 V Utilisation category DC-12 : 2.5 A network: DC at 48 V Utilisation category DC-14 : 0.03 A network: DC at 250 V Utilisation category DC-14 : 0.05 A network: DC at 110 V Utilisation category DC-14 : 0.2 A network: DC at 48 V Utilisation category DC-14 : 1 A network: DC at 24 V Utilisation category AC-12 : 5 A network: AC 50/60 Hz at 110 V Utilisation category AC-12 : 5 A network: AC 50/60 Hz at 220/240 V Utilisation category AC-12 : 5 A network: AC 50/60 Hz at 250 V Utilisation category AC-12 : 5 A network: AC 50/60 Hz at 380/440 V Utilisation category AC-12 : 5 A network: AC 50/60 Hz at 48 V Utilisation category AC-12 : 5 A network: AC 50/60 Hz at 480 V Utilisation category AC-15 : 0.1 A network: AC 50/60 Hz at 480 V Utilisation category AC-15 : 1.5 A network: AC 50/60 Hz at 380/440 V Utilisation category AC-15 : 2 A network: AC 50/60 Hz at 220/240 V Utilisation category AC-15 : 2.5 A network: AC 50/60 Hz at 110 V Utilisation category AC-15 : 3 A network: AC 50/60 Hz at 24 V Utilisation category AC-15 : 3 A network: AC 50/60 Hz at 48 V Utilisation category DC-12 : 5 A network: DC at 24 V
Minimum load	1 mA at 4 V DC
Accessory / separate part category	Spare part Compact NS630b...1600 Spare part Compact NS1600b...3200

Environment

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.