



### Main

Range	TeSys
Device short name	LTMCU
Product or component type	Operator control unit
Range compatibility	TeSys T, LTMR motor controller
Display type	Backlit LCD
Local signalling	4 LEDs
Control button type	10 push-button(s)
Device connection	Connection to a LTM R controller, RJ45 connector on rear Connection to a PC, RJ45 connector on front

### Complementary

Supply	Via the controller
Supply current	<= 140 mA
Power dissipation	1 W
Standards	EN/IEC 61131-2 CSA C22.2 No 60947-4-1 UL 60947-4-1A
Product certifications	CE CSA C-Tick NOM UL EAC
Electromagnetic compatibility	Electrostatic discharge immunity, level 3 (8 kV air, 4 kV contact) conforming to EN/IEC 61000-4-2 Radiated RF fields immunity, level 3 (10 V/m) conforming to EN/IEC 61000-4-3 Conducted RF disturbances immunity, level 3 (10 V) conforming to EN/IEC 61000-4-6 Surges immunity, level 3 (2 kV) conforming to EN/IEC 61000-4-5 Fast transient bursts immunity, level 3 (2 kV) conforming to EN/IEC 61000-4-4
IP degree of protection	IP54 on front IP20 on rear
Mounting mode	Flush-mounted
Width	117 mm
Height	70 mm
Depth	50 mm
Product weight	0.4 kg

### Environment

ambient air temperature for operation	-20...60 °C
ambient air temperature for storage	-40...80 °C
relative humidity	15...95 %
protective treatment	TC (12 humidity cycles at 55 °C) conforming to EN/IEC 60068-2-30
mechanical robustness	Shocks resistance (15 Gn for 11 ms) conforming to EN/IEC 60068-2-27 Vibrations resistance (4 Gn, 5...300 Hz) conforming to EN/IEC 60068-2-6
fire resistance	650 °C conforming to EN/IEC 60947-1
flame retardance	V2 conforming to UL 94

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.