

HANECO WEATHERPROOF LED BATTEN INSTALLATION GUIDE

DURA^{FOREMAN}




Please read these installation instructions carefully before installing or maintaining this equipment. The product is designed for installation and maintenance in accordance with relevant Australian standards (AS/NZS3000), by an authorised and licensed electrician. The installation instructions were correct at the time of print. To reflect changes in technology and Australian and New Zealand standards; Haneco reserves the right to amend the instructions without notice. Updated guidelines can be found on relevant brand web site.

PRODUCT NAME: DURA^{FOREMAN} 1200mm Temporary Weatherproof Batten

Issue Date: 10/09/2024

Product code	DURA-12-FRMN	DURA-12-FRMN-EM
Power	36 W	36 W
CCT	4000 K	
Emergency	No	Yes
Lumens	4094 lm	4094 lm (EM 223 lm)
Beam angle	120°	
IP rating	IP65	
IK rating	IK08	
Projected Lifespan	>50,000hrs @ Ta 25°C (L70)	
Flicker-free	Yes	
Driver	Integral	
Nominal voltage & Frequency	220-240Vac,50/60Hz	
Power factor	> 0.9	
Surge protection rating	Overload / Short Circuit	
Inrush current	30A @ 190uS	
Rated operating ambient temperature	-15 to 40°C	0 to 40°C
Electrical connection	PA9 Terminals	
Installation type	Surface Mount / Suspended	
Warranty	1 yr	

Line diagrams and dimensions



DURA-12-FRMN
DURA-12-FRMN-EM



HANECO WEATHERPROOF LED BATTEN INSTALLATION GUIDE

DURA^{FOREMAN}

Fitting Code:





DURA-12-FRMN

DURA-12-FRMN-EM


Installation

To ensure correct function and safety, please read and follow all instructions carefully before using the product.


1. Turn off power supply before installation or before doing any maintenance work.
2. Do not install any luminaire near the heat source.
3. Do not exceed the nominal supply voltage or amperage ratings.
4. All wiring and installation of the light fitting must adhere to local and national wiring rules.
5. Take care not to pull any electrical wires during unpacking as this may damage the connection.
6. Lay out all the components on a smooth surface and make sure there are no components missing before assembling.
7. To avoid injury or damage to the fitting, please ensure that power leads and screws are secure before connecting the power.
8. Please keep instructions for future reference.
9. Please refer to IP(Ingress Protection) rating of this luminaire when deciding the location of installation.
10. The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed.
11. The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.



1. Drill a 6mm hole



3. Fix the luminaire with the brackets



2. According to the Fixing hole centre, installation expansion bolts and screws, install the bracket.



4. Finish installation