

LA1DY20

TeSys D - auxiliary contact block - 2 NO - screw clamp terminals



Main

Range of product	TeSys D TeSys D control relay TeSys F
Range	TeSys
Device short name	LA1
Product or component type	Auxiliary contact block
Auxiliary contacts operation	Instantaneous
Pole contact composition	2 earth screen continuity poles 2 NO (sealed)
Connections - terminals	Screw clamp terminals 1 cable 1...2.5 mm ² - cable stiffness: flexible - with cable end Screw clamp terminals 1 cable 1...2.5 mm ² - cable stiffness: flexible - without cable end Screw clamp terminals 2 cable 1...2.5 mm ² - cable stiffness: flexible - with cable end Screw clamp terminals 2 cable 1...2.5 mm ² - cable stiffness: flexible - without cable end Screw clamp terminals 1 cable 1...2.5 mm ² - cable stiffness: solid Screw clamp terminals 2 cable 1...2.5 mm ² - cable stiffness: solid
Quantity per set	Set of 2

Complementary

Mounting location	Front
[Ui] rated insulation voltage	250 V - conforming to IEC 60947-5-1
[Ue] rated operational voltage	<= 24 V
Mechanical durability	5 Mcycles
Minimum switching current	0.3 mA
Minimum switching voltage	3 V
Insulation resistance	> 10 MOhm
Product weight	0.04 kg

Environment

environmental characteristic	Harsh environment
standards	IEC 60947-5-1 VDE 0660
product certifications	CSA UL
IP degree of protection	IP2x conforming to VDE 0106
protective treatment	TH conforming to IEC 60068
ambient air temperature for operation	-25...70 °C
ambient air temperature for storage	-25...70 °C

Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 0944 - Schneider Electric declaration of conformity
REACH	Reference not containing SVHC above the threshold
Product environmental profile	Available

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

