



### Main

Range	TeSys
Device short name	LA1SK
Product or component type	Auxiliary contact block
Product compatibility	LC1SK
Auxiliary contacts operation	Instantaneous
Pole contact composition	2 NC
Connections - terminals	Screw clamp terminals 2 cable 1.5...4 mm <sup>2</sup> - cable stiffness: solid Screw clamp terminals 1 cable 1.5...6 mm <sup>2</sup> - cable stiffness: solid Screw clamp terminals 1 cable 0.5...6 mm <sup>2</sup> - cable stiffness: flexible - with cable end Screw clamp terminals 2 cable 0.35...2.5 mm <sup>2</sup> - cable stiffness: flexible - with cable end Screw clamp terminals 1 cable 0.35...6 mm <sup>2</sup> - cable stiffness: flexible - without cable end Screw clamp terminals 2 cable 0.35...1.5 mm <sup>2</sup> - cable stiffness: flexible - without cable end

### Complementary

Mounting location	Front side
[Ui] rated insulation voltage	690 V - conforming to BS 5424 690 V - conforming to IEC 60947 690 V - conforming to VDE 0110 group C 690 V - conforming to CSA C22.2 No 14
[Ue] rated operational voltage	690 V AC <= 400 Hz
[Ith] conventional free air thermal current	10 A at <= 55 °C
Associated fuse rating	IEC 60947 VDE 0660
Tightening torque	0.8 N.m - on screw clamp terminals
Width	27 mm
Product weight	0.022 kg

### Environment

standards	BS 5424 IEC 60947 NF C 63-110 VDE 0660
product certifications	CSA UL
IP degree of protection	IP2x
protective treatment	TC conforming to IEC 60068
ambient air temperature for operation	-20...50 °C
ambient air temperature for storage	-50...70 °C
operating altitude	2000 m without derating in temperature

### Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 0718 - Schneider Electric declaration of conformity
REACH	Reference not containing SVHC above the threshold
Product environmental profile	Available

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

