# Product data sheet Characteristics

# ZB5AG08

# selector switch head Ø22 3-position spring return Ronis 455



#### Main

Commercial Status	Commercialised
Range of product	Harmony XB5
Product or component type	Head for key selector switch
Device short name	ZB5
Bezel material	Plastic
Mounting diameter	22 mm
Sale per indivisible quantity	1
Shape of signaling unit head	Round
Type of operator	Spring return right to centre
Operator profile	Black key switch
Operator position information	3 positions +/- 45°
Type of keylock	Ronis 455
Key withdrawal position	Left

### Complementary

CAD overall width	29 mm	
CAD overall height	29 mm	
CAD overall depth	62 mm	
Product weight	0.057 kg	
Mechanical durability	1000000 cycles	
Main group	Selector switch	
Group of product	Key switch	
Maximum of contact NO or NC	6	
Station name	XALK 25 cut-outs	
	XALD 15 cut-outs	

#### Environment

Protective treatment	TH	
Ambient air temperature for storage	-4070 °C	
Ambient air temperature for operation	-2570 °C	
Class of protection against electric shock	Class II conforming to IEC 60536	
IP degree of protection	IP69 K conforming to IEC 60529	
NEMA degree of protection	NEMA 4X NEMA 13	
Resistance to high pressure washer	7000000 Pa at 55 °C,distance: 0.1 m	
IK degree of protection	IK06 conforming to IEC 50102	
Standards	CSA C22-2 No 14 EN/IEC 60947-1 EN/IEC 60947-5-1 EN/IEC 60947-5-4 EN/IEC 60947-5-5 JIS C 4520 UL 508	

Product certifications	BV
	CSA
	DNV
	GL
	LROS (Lloyds register of shipping)
	RINA
	UL listed
Vibration resistance	5 gn (f = 2500 Hz) conforming to IEC 60068-2-6
Shock resistance	50 gn for 11 ms half sine wave acceleration conforming to IEC 60068-2-27 30 gn for 18 ms half sine wave acceleration conforming to IEC 60068-2-27

# Product data sheet Dimensions Drawings

# ZB5AG08

### Dimensions of Heads for Selector Switches

## Standard Handle Operator

ZB5 AD•, ZB5 AD•M







## Long Handle Operator

ZB5 AJ•, ZB5 AJ•M







#### Black Knurled Knob

ZB5 AD•9


mm





### Key Switch (Ronis n° 455)

ZB5 AG•, ZB5 AG0•, ZB5 AG•M






## Key Switch (DOM n° 8D1)

ZB5 AGD








# ZB5AG08

### Panel Cut-out for Pushbuttons, Switches and Pilot Lights (Finished Holes, Ready for Installation)


### Connection by Screw Clamp Terminals or Plug-in Connectors or on Printed Circuit Board



- Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5 AZ902 is recommended.  $\varnothing$ 22.5 mm recommended ( $\varnothing$ 22.3  $_0$   $^{+0.4}$ ) /  $\varnothing$ 0.89 in. recommended ( $\varnothing$ 0.88 in.  $_0$   $^{+0.016}$ )

Connections	a in mm	a in in.	b in mm	b in in.
By screw clamp terminals or plug-in connector	40	1.57	30	1.18
By Faston connectors	45	1.77	32	1.26
On printed circuit board	30	1.18	30	1.18


### **Detail of Lug Recess**



- (1) Diameter on finished panel or support
- For selector switches and Emergency stop buttons, use of an anti-rotation plate type ZB5 AZ902 is recommended.  $\varnothing$ 22.5 mm recommended ( $\varnothing$ 22.3  $_0^{+0.4}$ ) /  $\varnothing$ 0.89 in. recommended ( $\varnothing$ 0.88 in.  $_0^{+0.016}$ )

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

## Panel Cut-outs (Viewed from Installer's Side)



A: 30 mm min. / 1.18 in. min. B: 40 mm min. / 1.57 in. min.


# Printed Circuit Board Cut-outs (Viewed from Electrical Block Side)

Dimensions in mm



A: 30 mm min. B: 40 mm min.

#### Dimensions in in.



A: 1.18 in. min. B: 1.57 in. min.


#### General Tolerances of the Panel and Printed Circuit Board

The cumulative tolerance must not exceed 0.3 mm / 0.012 in.: T1 + T2 = 0.3 mm max.

#### Installation Precautions

- Minimum thickness of circuit board: 1.6 mm / 0.06 in.
- Cut-out diameter: 22.4 mm ± 0.1 / 0.88 in. ± 0.004
- Orientation of body/fixing collar ZB4 BZ009: ± 2°30' (excluding cut-outs marked a and b).
- Tightening torque of screws ZBZ 006: 0.6 N.m (5.3 lbf.in) max.
- Allow for one ZB4 BZ079 fixing collar/pillar and its fixing screws:
  - o every 90 mm / 3.54 in. horizontally (X), and 120 mm / 4.72 in. vertically (Y).
  - o with each selector switch head (ZB5 AD•, ZB5 AJ•, ZB5 AG•).

The fixing centers marked a and b are diagonally opposed and must align with those marked 4 and 5.



- (1) Head ZB5 AD•
- (2) Panel
- (2) Nut
- (4) Printed circuit board

#### Mounting of Adapter (Socket) ZBZ 01•

- 1 2 elongated holes for ZBZ 006 screw access
- 2 1 hole Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 for centring adapter ZBZ 01•
- 3 8 × Ø 1.2 mm / 0.05 in. holes
- 4 1 hole Ø 2.9 mm ± 0.05 / 0.11 in. ± 0.002, for aligning the printed circuit board (with cut-out marked a)
- 5 1 elongated hole for aligning the printed circuit board (with cut-out marked b)
- 6 4 holes Ø 2.4 mm / 0.09 in. for clipping in adapter ZBZ 01•

Dimensions An + 18.1 relate to the Ø 2.4 mm ± 0.05 / 0.09 in. ± 0.002 holes for centring adapter ZBZ 01•.				