K50K006YP

cam reversing star-delta switch - 3-pole - 45° - 50 A - screw mounting



Main

Range of product	Harmony K
Product or component type	Complete cam switch
Component name	K50
[lth] conventional free air thermal current	50 A
Mounting location	Front
Fixing mode	4 holes
Cam switch head type	With front plate 64 x 64 mm
Type of operator	Black handle
Rotary handle padlocking	Without
Presentation of legend	With metallic legend, delta - Y - 0 - Y - delta black marking
Cam switch function	Reversing star-delta switch
Return	Without
Off position	With Off position
Poles description	3P
Switching positions	Left: 0° - 315° - 270° Right: 0° - 45° - 90°
IP degree of protection	IP40 conforming to IEC 529 IP40 conforming to NF C 20-010

Complementary

Complementary	
Switching angle	45 °
[Ui] rated insulation voltage	690 V degree of pollution 3 conforming to EN/IEC 60947-1
Short-circuit current	5000 A
Short-circuit protection	63 A by cartridge fuse, type gG
[Uimp] rated impulse withstand voltage	6 kV conforming to EN/IEC 60947-1
Contact operation	Slow-break
Positive opening	With
Electrical connection	Captive screw clamp terminals flexible, 2 x 6 mm ² Captive screw clamp terminals solid, 2 x 10 mm ²
Tightening torque	2 N.m
Switching capacity in mA	15000 mA DC at 120 V 2 contact(s) for inductive load (T = 50 ms) 15000 mA DC at 180 V 3 contact(s) for inductive load (T = 50 ms) 15000 mA DC at 60 V 1 contact(s) for inductive load (T = 50 ms) 20000 mA DC at 140 V 3 contact(s) for inductive load (T = 50 ms) 20000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms) 20000 mA DC at 95 V 2 contact(s) for inductive load (T = 50 ms) 30000 mA DC at 30 V 1 contact(s) for inductive load (T = 50 ms) 30000 mA DC at 60 V 2 contact(s) for inductive load (T = 50 ms) 30000 mA DC at 90 V 3 contact(s) for inductive load (T = 50 ms) 30000 mA DC at 110 V 1 contact(s) for inductive load (T = 50 ms) 3500 mA DC at 220 V 2 contact(s) for inductive load (T = 50 ms) 3500 mA DC at 330 V 3 contact(s) for inductive load (T = 50 ms) 3500 mA DC at 120 V 2 contact(s) for resistive load (T = 1 ms) 37000 mA DC at 180 V 3 contact(s) for resistive load (T = 1 ms) 37000 mA DC at 140 V 3 contact(s) for resistive load (T = 1 ms) 40000 mA DC at 24 V 1 contact(s) for resistive load (T = 50 ms) 40000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms) 40000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms) 40000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms) 40000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms) 40000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms) 40000 mA DC at 48 V 1 contact(s) for inductive load (T = 50 ms) 40000 mA DC at 48 V 2 contact(s) for inductive load (T = 1 ms) 50000 mA DC at 48 V 2 contact(s) for resistive load (T = 1 ms)


Mechanical durability	300000 cycles
CAD overall width	64 mm
CAD overall height	64 mm
CAD overall depth	173 mm
Product weight	0.69 kg

Environment

standards	EN/IEC 60947-3		
product certifications	CULus 120 V 3 hp 1 phase		
	CULus 480 V 25 hp 3 phases		
	CULus 240 V 7.5 hp 1 phase		
	CULus 240 V 7.5 hp 3 phases		
protective treatment	TC		
ambient air temperature for operation	-2555 °C		
ambient air temperature for storage	-4070 °C		
overvoltage category	Class II conforming to IEC 60536		
	Class II conforming to NF C 20-030		

Dimensions

Front Mounting




e support panel thickness 0.5 to 5.5 mm / 0.02 to 0.22 in in.

а		b		С		D1	
mm	in.	mm	in.	mm	in.	mm	in.
133.3	5.25	60	2.36	64	2.52	4.1	0.16

Panel Cut-Out


Front Mounting



D2		D3		G1	
mm	in.	mm	in.	mm	in.
4.5	0.18	10	0.39	48	1.89



Link Positions (Factory Mounted)




Marking



Angular Position of Switch

Switching Program



Convention Used for Switching Program Representation

Contact closed

Contact closed in 2 positions and maintained between the 2 positions

Sealed assembly for auto-maintain control

Overlapping contacts

Spring return position: for a switching angle of 90°, spring return is over 30° after the last position (for a maximum of 3 simultaneous contacts).

Example:

