

Product No: MS132-32

ABB MS132-32 MANUAL MOTOR STARTER 25 ... 32 A MS132-32

FEATURES

- Compact design, ideal for installations with limited space
- Provides reliable protection against short-circuits, overload and phase failures
- High breaking capacity
- Features a lockable rotary handle with clear switch position indication
- Suitable for both 3 phase and single phase applications



General Information	
Brand	ABB
Product Type	Manual Motor Starter
Technical Attributes	
Design of Control Element	Turn Button
Breaking Capacity 400V AC - Icu (kA)	50
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	25
Phase Failure Sensitive	Yes
Power Loss (W)	9.3
Rated Instantaneous Short-Circuit Current - Ii (A)	480
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	32
Rated Operational Power AC-3 400V (kW)	15
Rated Operational Voltage AC (V)	690
Rated Operational Voltage DC (V)	250
Rated Uninterrupted Current - Iu (A)	32
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals



Thermal Current Setting Range (A)	25.0 – 32.0
Thermal Overload Protection	Yes

Dimensions	
Dimensions (mm)	45W x 97.8H x 86.55D

Protection & Standards	
Degree of Protection	IP20

Resources	
Product catalogue (Flipbook)	Download from here