

## Features and Benefits

- » Designed to ensure that you position and angle your digital TV antenna/satellite in the correct direction for best reception
- » Suitable for the home, caravan, boating and leisure enthusiast
- » Provides LED lights to show signal strength for antenna/satellite adjustment
- » Easy to use, compact design
- » Includes 9V battery

## Test Equipment

Matchmaster has a range of test equipment from the simple signal finders through to professional highend RF/Fibre optic analysers. Matchmaster can supply hands on training for all meter types as well as local service and repairs. All professional meters are tested and programmed by Matchmaster to your needs.



## 12MM-DF03 Specifications

Frequency	FTA 40-860MHz SAT, 950-2150MHz	
Sensitivity	ANT input, 4 channels/MUX's, +/-2dB $\mu$ V, 75 Ohm (single channel sensitivity in square brackets)	
1 LED	44 (63) dB $\mu$ V	Low signal
2 LED's	47 (66) dB $\mu$ V	Minimum signal
3 LED's	51 (69) dB $\mu$ V	
4 LED's	54 (72) dB $\mu$ V	Optimum signal
5 LED's	59 (75) dB $\mu$ V	
6 LED's	61 (78) dB $\mu$ V	
7 LED's	64 (81) dB $\mu$ V	
8 LED's	68 (84) dB $\mu$ V	
9 LED's	71 (87) dB $\mu$ V	
10 LED's	74 (90) dB $\mu$ V	Strong signal
11 LED's	78 (94) dB $\mu$ V	
12 LED's	81 (98) dB $\mu$ V	
SAT Input	Visual/Audio Indication Only	