



Main

| | |
|--------------------------------|---|
| Range | Acti 9 |
| Product or component type | Shunt trip release with OC contact |
| Device short name | IMX+OF |
| Signal contacts composition | 1 C/O |
| [Ie] rated operational current | AC-12 : 3 A at 415 V AC - 50 Hz AC-12 : 6 A at 100 V AC - 50 Hz AC-12 : 6 A at 230 V AC - 50 Hz DC-12 : 1 A at 110 V DC DC-12 : 1 A at 130 V DC |
| Control circuit voltage | 100 V AC 50/60 Hz 110 V DC 130 V DC 230 V AC 50/60 Hz 415 V AC 50/60 Hz |
| 9 mm pitches | 2 |

Complementary

| | |
|-------------------------|---|
| Local signalling | Action indicator |
| Mounting mode | Clip-on |
| Mounting support | DIN rail |
| Width | 18 mm |
| Colour | White |
| Connections - terminals | Clamp terminal 1 cable(s) 6 mm ² rigid Clamp terminal 2 cable(s) 2.5 mm ² rigid Clamp terminal 1 cable(s) 4 mm ² flexible Clamp terminal 2 cable(s) 2.5 mm ² flexible with cable end cable end |
| Tightening torque | 1 N.m |

Environment

| | |
|---------------------------------------|----------------------------------|
| standards | EN/IEC 60947-5-1 |
| tropicalisation | 2 conforming to EN/IEC 60947-5-1 |
| relative humidity | 95 % at 55 °C |
| ambient air temperature for operation | -25...50 °C |
| ambient air temperature for storage | -40...85 °C |

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1216 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.