



Main

| | |
|---------------------------|--------------------------|
| Product name | Easy56 |
| Product or component type | Switch and socket-outlet |
| Device short name | EY56C520 |
| Plug, socket category | Low voltage |
| Poles description | 3P + N + E |
| Control type | Rotary knob |
| Rotary handle padlocking | 2 padlocks x Ø 8 mm |
| Network type | AC |
| Outlet standard | Australian/New Zealand |

Complementary

| | |
|-------------------------------------|---|
| Mounting mode | Surface mounted |
| Plug, socket, control station shape | Straight |
| [In] rated current | 20 A |
| Pin number | 5 pins |
| Shape of pin | Tubular |
| [Ue] rated operational voltage | 500 V |
| Network frequency | 50 Hz |
| Protection type | Without protection |
| Material | Polycarbonate |
| Contacts material | Brass pins : |
| Connections - terminals | Screw terminals |
| Cable cross section | 1...16 mm ² |
| Cable entry number | 2 x M25 1 x M32 |
| Product weight | 0.82 kg |
| Height | 203 mm |
| Width | 101 mm |
| Depth | 101 mm |
| Colour | Grey RAL 7035 body Dark grey rotary handle |

Environment

| | |
|---------------------------------------|-----------------------------|
| standards | AS/NZS 3123 AS/NZS 3133 |
| IP degree of protection | IP66 conforming to AS 60529 |
| ambient air temperature for operation | -25...75 °C |
| ambient air temperature for storage | -25...75 °C |

Offer Sustainability

| | |
|--------------------------|---------------------------|
| Sustainable offer status | Not Green Premium product |
|--------------------------|---------------------------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.