



Main

| | |
|---------------------------|---------------------|
| Product name | Easy56 |
| Device short name | EY56SW120 |
| Product or component type | Switch |
| Poles description | 1P |
| Control type | Rotary knob |
| Rotary handle padlocking | 2 padlocks x Ø 8 mm |

Complementary

| | |
|--|--|
| [Ue] rated operational voltage | 250 V AC 50 Hz |
| [Uimp] rated impulse withstand voltage | 2.5 kV conforming to IEC 60947-3 according to IEC 60947-3 conforming to IEC 60947-3 IEC 60947-3 conforming to IEC 60947-3 conforming to IEC 60947-3 IEC 60947-3 2.5 kV conforming to AS/NZS 3133 according to AS/NZS 3133 conforming to AS/NZS 3133 AS/NZS 3133 conforming to AS/NZS 3133 conforming to AS/NZS 3133 AS/NZS 3133 |
| [Ithe] conventional enclosed thermal current | 20 A |
| [Ie] rated operational current | 20 A AC-21A at 250 V AC 20 A AC-23A at 250 V AC |
| Making capacity | 200 A at 250 V AC-21A 200 A at 250 V AC-23A |
| [Icm] rated short-circuit making capacity | 1 kA at 250 V (AC-21A) 1 kA at 250 V (AC-23A) |
| [Icw] rated short-time withstand current | 1.5 kA at 250 V duration: 1 s |
| Breaking capacity | 0.2 kA at 250 V (AC-21A) 0.2 kA at 250 V (AC-23A) |
| Suitability for isolation | Yes |
| Connections - terminals | Screw terminals cable 1...16 mm ² - cable stiffness: rigid or stranded - |
| Height | 101 mm |
| Width | 101 mm |
| Depth | 101 mm |
| Product weight | 0.471 kg |
| Colour | Grey RAL 7035 body Dark grey rotary handle |

Environment

| | |
|---------------------------------------|-----------------------------|
| standards | AS/NZS 3133 |
| IP degree of protection | IP66 conforming to AS 60529 |
| ambient air temperature for operation | -25...75 °C |

Offer Sustainability

| | |
|--------------------------|---------------------------|
| Sustainable offer status | Not Green Premium product |
|--------------------------|---------------------------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.