



Main

| | |
|-------------------------------|------------------------------|
| Range | Clipsal Iconic |
| Product or component type | Socket |
| Device presentation | Grid plate with skin |
| Outlet poles configuration | 1P + E with shutter |
| Provided equipment | Screws Grid plate Skin |
| Fixing mode | By screws (horizontal) |
| Type of packing | Polybag |
| Quantity per set | Set of 10 |
| Sale per indivisible quantity | 1 |
| Rated current | 10 A, 250 V AC, 50 Hz |

Complementary

| | |
|---------------------------------------|--|
| Number of power socket outlets | 2 |
| Device mounting | Flush |
| Outlet standard description | With earthing contact |
| Outlet standard | Australian/New Zealand |
| Ground lug position | Straight 180° position |
| Colour tint | Vivid white (VW) |
| Surface finish | Matt |
| Ambient air temperature for operation | 0...45 °C |
| Relative humidity | 10...95 % |
| Electrical durability | 12000 cycles |
| Connections - terminals | 3 x screw terminals |
| Screwdriver shape | Philips No 2 Square drive no 1 (SQ1) |
| Number of cables | 1...4 |
| Clamping connection capacity | 2.5 mm ² (stranded) 2.5 mm ² (flexible) 2.5 mm ² (rigid) |
| Wire stripping length | 16 mm |
| Material | PC (polycarbonate) for grid plate PP (polypropylene) for flaps POM (polyoxymethylene) for shutter PC (polycarbonate) for skin ABS (acrylonitrile butadiene-styrene) for skin |
| Height | 120 mm |
| Width | 78 mm |
| Depth | 32 mm |
| Embedding depth | 18 mm |
| Product weight | 0.116 kg |
| Standards | AS/NZS 3112 |

Environment

| | |
|------------------------|-----|
| product certifications | RCM |
|------------------------|-----|

Offer Sustainability

| | |
|--------------------------|---------------------------|
| Sustainable offer status | Not Green Premium product |
|--------------------------|---------------------------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

