

single function relay, Harmony Timer Relays, 8A, 2CO, 0.1s...100h, multifunction, 12V AC DC

RE22R2MJU

Main

Range of product	Harmony Timer Relays
Discrete output type	Relay
Product or component type	Modular timing relay
Device short name	RE22
Nominal output current	8 A

Complementary

Contacts type and composition	1 C/O timed contact 1 C/O timed or instantaneous contact
Time delay type	Power on-delay On-delay and off-delay Interval Off-delay Symmetrical flashing
Time delay range	110 min 660 min 0.11 s 660 s 110 s 110 h 10100 h
Control type	Rotary knob front panel
[Us] rated supply voltage	12 V AC/DC
Voltage range	0.91.2 Us
Supply frequency	5060 Hz +/- 5 %
Connections - terminals	Screw terminals, 2 x 1.5 mm² with cable end Screw terminals, 2 x 2.5 mm² without cable end
Tightening torque	0.61 N.m conforming to IEC 60947-1
Housing material	Self-extinguishing
Repeat accuracy	+/- 0.5 % conforming to IEC 61812-1
Temperature drift	+/- 0.05 %/°C
Voltage drift	+/- 0.2 %/V
Setting accuracy of time delay	+/- 10 % of full scale at 25 °C conforming to IEC 61812-1

Width	22.5 mm
Function available	A- Power on-delay relay-2 C/O Ac- On-delay and off-delay relay w/ control signal-2 C/O At- Power on-delay relay w/ pause/summation (Y1)-2 C/O B- Single interval relay w/ control signal-2 C/O Bw- Double interval relay w/ control signal-2 C/O C- Off-delay relay w/ control signal-2 C/O D- Symmetrical flashing relay (starting pulse-off)-2 C/O Di- Symmetrical flashing relay (starting pulse-on)-2 C/O H- Interval relay-2 C/O Ht- Interval relay w/ pause/summation (Y1)-2 C/O
Status LED	LED green (flashing) for timing in progress LED green (steady) for power ON LED yellow for relay energised
Mounting support	35 mm DIN rail conforming to IEC 60715
Mounting position	Any position in relation to normal vertical mounting plane
Safety reliability data	B10d = 190000 MTTFd = 205.4 years
Power on delay	100 ms
Rated impulse withstand voltage	5 kV for 1.250 μs conforming to IEC 60664-1 5 kV conforming to IEC 61812-1
Mechanical durability	10000000 cycles
Electrical durability	100000 cycles for resistive load, 8 A at 250 V, AC
Maximum switching voltage	250 V
Maximum switching current	8 mA
Minimum switching current	10 mA at 5 V
Breaking capacity	2000 VA
Power consumption in W	0.5 W at 12 V DC
Immunity to microbreaks Power consumption in VA	10 ms 1.2 VA at 12 V AC
Recovery time	120 ms on de-energisation
Insulation resistance	100 MOhm at 500 V DC conforming to IEC 60664-1
Control signal pulse width	30 ms 100 ms under load
Time delay type	Power on-delay - A- Power on-delay relay On-delay and off-delay - Ac- On-delay and off-delay relay w/ control signal Power on-delay - At- Power on-delay relay w/ pause/summation (Y1) Interval - B- Single interval relay w/ control signal Interval - Bw- Double interval relay w/ control signal Off-delay - C- Off-delay relay w/ control signal Symmetrical flashing - D- Symmetrical flashing relay (starting pulse-off) Symmetrical flashing - Di- Symmetrical flashing relay (starting pulse-on) Interval - H- Interval relay Interval - Ht- Interval relay w/ pause/summation (Y1)

Environment

Dielectric strength 2.5 kV for 1 mA/1 minute at 50 Hz conforming to IEC 61812-1

Standards	IEC 61000-6-1
	IEC 61812-1
	IEC 61000-6-4
	IEC 61000-6-3
	IEC 61000-6-2
Directives	2006/95/EC - low voltage directive
	2004/108/EC - electromagnetic compatibility
Product certifications	CSA
	cULus
	CE
	EAC
	GL
	CCC
	RCM
Ambient air temperature for operation	-2060 °C
Ambient air temperature for storage	-3060 °C
IP degree of protection	IP40 housing: conforming to IEC 60529
	IP20 terminal block: conforming to IEC 60529
	IP40 front face: conforming to IEC 60529
Vibration resistance	20 m/s² (f= 10150 Hz) conforming to IEC 60068-2-6
Shock resistance	15 gn for 11 ms conforming to IEC 60068-2-27
Relative humidity	93 %, without condensation conforming to IEC 60068-2-30
Electromagnetic compatibility	Electrostatic discharge immunity test - test level: 6 kV level 3 (contact discharge)
	conforming to IEC 61000-4-2
	Electrostatic discharge immunity test - test level: 8 kV level 3 (air discharge)
	conforming to IEC 61000-4-2 Fast transients immunity test - test level: 1 kV level 3 (capacitive connecting clip)
	conforming to IEC 61000-4-4
	Fast transients immunity test - test level: 2 kV level 3 (direct contact) conforming to IEC 61000-4-4
	Surge immunity test - test level: 1 kV level 3 (differential mode) conforming to IEC 61000-4-5
	Surge immunity test - test level: 2 kV level 3 (common mode) conforming to IEC 61000-4-5
	Radiated radio-frequency electromagnetic field immunity test - test level: 10 V level 3
	(0.1580 MHz) conforming to IEC 61000-4-6
	Electromagnetic field immunity test - test level: 10 V/m level 3 (80 MHz1 GHz) conforming to IEC 61000-4-3
	Immunity to microbreaks and voltage drops - test level: 30 % (500 ms) conforming to
	IEC 61000-4-11
	Immunity to microbreaks and voltage drops - test level: 100 % (20 ms) conforming to IEC 61000-4-11
	Conducted and radiated emissions class B conforming to EN 55022

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.700 cm
Package 1 Width	8.400 cm
Package 1 Length	9.700 cm
Package 1 Weight	103.000 g
Unit Type of Package 2	S02
Number of Units in Package 2	40
Package 2 Height	15.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	4.638 kg



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

∅ Environmental footprint		
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	19	

Use Better


⊗ Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	7bdc2711-0ad2-427c-8ece-532c5e9f09d7
REACh Regulation	REACh Declaration


Use Again

☼ Repack and remanufacture		
Take-back	No	

Dimensions Drawings

Dimensions






Product datasheet


RE22R2MJU

Connections and Schema

Internal Wiring Diagram



Wiring Diagram




Technical Description

Function A : Power on Delay Relay

Description

The timing period T begins on energization. After timing, the output(s) relay close(s).




Function Ac: On- and Off-Delay Relay with Control Signal

Description

After power-up, closing of the control contact Y1 causes the timing period T to start (timing can be interrupted by operating the Gate control contact G). At the end of this timing period, the relay closes.

When control contact Y1 re-opens, the timing T starts.At the end of this timing period T


At the end of this timing period T, the output reverts to its initial position (timing can be interrupted by operating the Gate control contact G).



Function At: Power on Delay Relay (Summation) with Control Signal

Description

After power-up, the first opening of control contact Y1 starts the timing. Timing can be interrupted each time control contact closes. When the cumulative total of time periods elapsed reaches the pre-set value T, the output relay closes.




T = t1+t2+t3

Function B : Interval Relay with Control Signal

Description


After power-up, pulsing or maintaining control contact Y1 starts the timing T. The output relay closes for the duration of the timing period T then reverts to its initial state.



Function Bw : Double Interval Relay with Control Signal

Description


On closing and opening of control contact Y1, the output relay closes for the duration of the timing period T.



Function C : Off-Delay Relay with Control Signal

Description

After power-up and closing of the control contact Y1, the output relay closes. When control contact Y1 re-opens, timing T starts. At the end of the timing period, the output(s) relay revert(s) to its/their initial state.




Function D : Symmetrical Flasher Relay (Starting Pulse Off)

Description

14

Repetitive cycle with two timing periods T of equal duration, with output(s) relay changing state at the end of each timing period T.




Before power-up Y1 should be permanently connected to A1. 2 timed outputs (R1/R2) or 1 timed output (R1) and 1 instantaneous output (R2 inst.)

Function D : Symmetrical Flasher Relay (Starting Pulse On)

Description


Repetitive cycle with two timing periods T of equal duration, with output(s) relay changing state at the end of each timing period T.



Function H : Interval Relay

Description

On energization of the relay, timing period T starts and the output(s) relay close(s). At the end of the timing period T, the output(s) relay revert(s) to its/their initial state



2 timed outputs (R1/R2) or 1 timed output (R1) and 1 instantaneous output (R2 inst.)

Legend

Relay de-energised	
Relay energised	
Output open	
Ou	utput closed
Y1 :	Control contact
R1/R2 :	2 timed outputs
R2 inst. :	The second output is instantaneous if the right position is selected
T:	Timing period
U:	Supply

Function Ht: Interval Relay & With Pause / Summation Control

Description

On energisation of power supply, output(s) R close(s) and timing period T starts.


The timing can be interrupted / paused each time X1 energizes.

When the cumulative total of time periods elapsed reaches the pre-set value T, the output(s) R revert(s) to its/their initial state Reenergization of X1 will also cause output(s) R close(s) if the time has elapsed and restart the same operation as described at the beginning.

Except for RE17*, RE22R2MMW, RENF22R2MMW, RE22R2MMU and RE22R2MJU, timing can be interrupted / paused each time Y1 energizes.


The second output (R2) can be either timed (when set to "TIMED" or instantaneous (when set to "INST").

Function: 1 Output




T = t1 + t2 +...

Function: 2 Outputs




T = t1 + t2 +...

Function: 1 Output with Retrigger / Restart Control



T = t1 + t2 +...

Function: 2 Outputs with Retrigger / Restart Control



T = t1 + t2 +...

Technical Illustration

Dimensions

