

# Product datasheet

Specifications



## APC Smart-UPS RT 192V 32x9Ah BP without Rail kit

SRTG192XLBP2

### Overview

Lead time Usually Ships within 2 Weeks

### Main

Product or component type	Battery
Number of rack unit	4U
Battery type	Lead-acid battery
Provided equipment	Installation guide Warranty card
Range of product	Smart-UPS Battery Systems

### Batteries & Runtime

Device mounting	Stand alone battery stack Rack mount
Number of battery filled slots	4
Number of battery free slots	0
Number of battery replacement quantity	2
Battery voltage	192 V

### Physical

Colour	Black
Height	17.5 cm
Width	44 cm
Depth	70.0 cm
Net weight	116 kg
Mounting mode	Rack-mounted
USB compatible	No

### Environmental

Ambient air temperature for operation	0...40 °C
Relative humidity	0...95 % non-condensing
Operating altitude	0...6600 ft
Storage Relative Humidity	0...95 % non-condensing
Storage altitude	0.000000000...15240.000000000 m

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	295 mm
Package 1 Width	790 mm
Package 1 Length	590 mm
Package 1 Weight	122.4 kg

## Contractual warranty

Warranty	2 years
----------	---------

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Carbon footprint (kg.eq.CO2 per CR, Total Life cycle) 560

Environmental Disclosure [Product Environmental Profile](#)

### Use Better

#### Materials and Substances

[EU RoHS Directive](#) Compliant

REACH Regulation [REACH Declaration](#)

### Use Again

#### Repack and remanufacture

Circularity Profile [End of Life Information](#)

Removable battery User replaceable

WEEE  The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Take-back No