Specifications



Easy UPS 3S High Capacity Battery String

E3SBTH4

Overview		
Presentation	High capacity battery string for use with Easy UPS 3S with internal battery slots and Easy UPS 3S Empty Modular Battery Cabinet (E3SXR6). Each battery string consists of four 9 Ah battery modules (E3SBTHU).	
Lead time	Usually Ships within 6 Weeks	
Main		
Product or component type	Battery module	
Range compatibility	Easy UPS 3M	
Battery type	VRLA	
Range of product	Easy UPS 3M	

Batteries & Runtime

Number of battery free slots	0
Number of battery filled slots	0
Device mounting	Enclosed battery cartridge
Battery voltage	120 V
battery power in VAh	9 VAh

Physical

•	
Height	15.7 cm
Width	42.8 cm
Depth	76 cm
Net weight	108 kg
Mounting mode	Not rack-mountable

Environmental

Ambient air temperature for operation	040 °C	
Operating altitude	03281 ft	
Relative humidity	095 % non-condensing	
Ambient air temperature for storage	-1540 °C	
Storage altitude	0.00000000015240.000000000 m	
Storage Relative Humidity	095 % non-condensing	

Packing Units

-	
Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	18.000 cm
Package 1 Width	56.000 cm
Package 1 Length	82.000 cm
Package 1 Weight	112.000 kg

C Environmental Data

Environmental Data explained >

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

How we assess product sustainability \geq				
onumber onumber				
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	1			
Environmental Disclosure	Product Environmental Profile			
Use Better				
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)			
REACh Regulation	REACh Declaration			
China RoHS Regulation	China RoHS declaration			
Use Again				
$^{\circlearrowright}$ Repack and remanufacture				
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins			

Take-back

No