

Product datasheet

Specifications



APC Smart-UPS SRT 192V 8 and 10kVA RM Battery Pack



SRT192RMBP2

Overview

Lead time	Usually in Stock
-----------	------------------

Main

Product or component type	Battery
Number of rack unit	3U
Battery type	Lead-acid battery
Provided equipment	Installation guide Warranty card Rack mounting brackets
Range of product	Smart-UPS Battery Systems

Batteries & Runtime

Number of battery free slots	0
Number of battery filled slots	0
Device mounting	Stand alone battery stack
Battery voltage	+/- 192 V
Number of battery replacement quantity	2
Replacement battery	APCRBC140

Physical

Colour	Black
Height	13 cm
Width	43.2 cm
Depth	68.27 cm
Net weight	91 kg
Mounting mode	Rack-mounted

Conformance

Standards	OSHPD
-----------	-------

Environmental

Ambient air temperature for operation	0...40 °C
Operating altitude	0...10000 ft

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Relative humidity	0...95 % non-condensing
Ambient air temperature for storage	-15...45 °C
Storage altitude	0.0000000000...15240.0000000000 m
Storage Relative Humidity	0...95 % non-condensing

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	42 cm
Package 1 Width	60 cm
Package 1 Length	100 cm
Package 1 Weight	105.5 kg

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

 Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	483
Environmental Disclosure	Product Environmental Profile

Use Better

 Materials and Substances	
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACH Regulation	REACH Declaration

Use Again

 Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable
Take-back	Yes