



2600 Running Watts*
3200 Starting Watts**



Model	P3200
Part Number	030854
Number of Outlets	3
Engine	Briggs & Stratton® OHV
Displacement	171cc
Amperage	15A
Voltage	230V AC
Auto Idle	Yes
Auto Voltage Regulation	Inverter

Fuel Tank Capacity (L)	5.7
Muffler	Yes - Spark Arrestor Type
Weight (Kg)	38.6
Low Oil Protection System	Yes
RCD	No
Dimensions L x W x H (cm)	66 x 35.2 x 51.7
Warranty Consumer	3 Years Limited Warranty ¹
Warranty Commercial	1 Year Limited Warranty ¹

- CO Guard™ - Shuts down your generator when harmful levels of carbon monoxide are detected
- QPT™ Quiet Power Technology - Automatically adjusts the engine speed further reducing noise and fuel consumption
- Easy Portability with telescopic handle and integrated wheels
- The PowerSmart Series Inverter Generators deliver 'pure sine waves' at 3200 watts peak and 2600 watts continuous making it ideal for sensitive electronic equipment
- StatStation™ Digital Display - Displays power usage, total unit lifetime hours, and maintenance reminders.
- Up to 8 hours run time @ 25% load

* Per CSA C22.2 No. 100-14 and ANSI/PGMA G300-2018

** Starting Watts is the maximum current that can momentarily be supplied when starting a motor, multiplied by the generator's rated voltage.

¹ See www.briggsandstratton.com for warranty details.

Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. Product may vary from images shown.