


Installation Guide – 147F Fire Rated Wall Boxes

Acoustic rated up to STC50 – fire rated one and two hours. Rating is dependent on strict adherence to installation instructions (refer test reports WFRA C91415). Use an appropriate water based fire resistant sealant to seal any gaps around box or to replace any intumescent material inadvertently removed.

Installation Instructions

1. Use box as a template to mark cut-out (refer to point 9 below for actual dimensions).
2. Cut opening in wall with care to ensure neat fit of the box.
3. Remove knockout for cable entry. If bringing cables through rear of box, slit intumescent material carefully with a sharp knife but **DO NOT REMOVE ANY MATERIAL**.
4. Feed cables into wallbox.
5. Ensure clamping arms are fully retracted into box.
6. Insert box into wall cut-out. Single gang only; fold down flap, insert box and restore flap after insertion.
7. Extend clamping arms, tighten screws until box is firmly fixed in position. **DO NOT OVERTIGHTEN**.
8. Gently tap retaining lugs until flush with wall face.
9. To ensure acoustic rating, fit gasket supplied.
Cat. No: 147F Cut-out size: 96 x 52mm



Head Office

33-37 Port Wakefield Road
Gepps Cross South Australia 5094

Email help@pdl.com.au

Website pdl.com.au

National Customer Care Enquiries
1300 2025 25

National Customer Care Facsimile
1300 2025 56

New Zealand & International Enquiries

You can find this brochure and many others online in PDF format at

pdl.com.au
pdl.co.nz



Schneider Electric (NZ) Ltd

PO Box 15355 New Lynn
Waitakere 0640
Auckland New Zealand

Freephone 0800 652 999
Telephone ++64 9 829 0490
Facsimile ++64 9 829 0491
Freefax 0800 101 152

Email sales@nz.schneider-electric.com
Website pdl.co.nz

Follow the links off the home page or access the following page directly
pdl.com.au/brochures.aspx
pdl.co.nz/brochures.aspx

Schneider Electric reserves the right to change specifications, modify designs and discontinue items without incurring obligation and whilst every effort is made to ensure that descriptions, specifications and other information in this instruction are correct, no warranty is given in respect thereof and the company shall not be liable for any error therein.

© Schneider Electric

This material is copyright under Australian and international laws. Except as permitted under the relevant law, no part of this work may be reproduced by any process without prior written permission of and acknowledgement to Schneider Electric.