

# 3 Wire Satellite and Terrestrial Multiswitch 3 In 8 Out 21MM-SMS38



*For the Best*

The 21MM-SMS38 is a 3-input, 8-output multiswitch designed to distribute terrestrial (FTA) and satellite horizontal and vertical services. The SMS38 is Foxtel approved for domestic and small commercial applications and is also perfect for use in VAST and any other KU band satellite distribution. The multiswitch is passive for Terrestrial services and active (remotely powered by the STB) for the Satellite feeds.

## Features and Benefits

- » Foxtel approval (F30046)
- » 8-way multiswitch for terrestrial (FTA), Foxtel, VAST and other satellite KU band services.
- » Remotely powered by the STB with 3dB satellite gain to help offset cable losses.
- » Passive pass-through for terrestrial (FTA) input with 15-18dB through loss
- » Connect up to 8 TV's or STB's (4 x when using Foxtel IQ series STB)
- » Low power consumption from STB of 60mA with maximum throughput current to LNB of 400mA
- » Simple plug and play, no tuning required



## 21MM-SMS38 Specifications

Foxtel Approval Number	F30046
Inputs	3
Outputs	8
FTA Frequency	5-862MHz
Sat Frequency	950-2150MHz
Gain Satellite	3dB
Loss Terrestrial	15-18dB
Maximum LNB Current Capacity	400mA
Dimension	152x100x42mm (WxHxD)
Weight	270g

