

Push button head, Harmony XAC, plastic, brown, booted, spring return

XACA9419

Main

Range of product	Harmony XAC	
Product or component type	Head for push-button	
Component name	XACA	

Complementary

•		
Marking	Unmarked	
Operator additional information	Booted	
Cap/operator or lens colour	Brown	
Product compatibility	XACA	
Mounting location	Front of enclosure	
Sale per indivisible quantity	10	
Standards	CSA C22.2 No 14 IEC 60204-32 UL 508 IEC 60947-5-1	
Ambient air temperature for operation	-2570 °C	
Ambient air temperature for storage	-4070 °C	
Vibration resistance	15 gn (f= 10500 Hz) conforming to IEC 60068-2-6	
Shock resistance	100 gn conforming to IEC 60068-2-27	
Overvoltage category	Class II conforming to IEC 61140	
IP degree of protection	IP65 conforming to IEC 60529	
IK degree of protection	IK08 conforming to IEC 62262	
Net weight	0.01 kg	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.000 cm
Package 1 Width	15.000 cm
Package 1 Length	3.000 cm
Package 1 Weight	9.000 g
Unit Type of Package 2	BB1
Number of Units in Package 2	10

Package 2 Height	4.000 cm
Package 2 Width	15.000 cm
Package 2 Length	12.000 cm
Package 2 Weight	96.000 g
Unit Type of Package 3	S02
Number of Units in Package 3	250
Package 3 Height	15.000 cm
Package 3 Width	30.000 cm
Package 3 Length	40.000 cm
Package 3 Weight	2.763 kg

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Total lifecycle Carbon footprint	1
Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
End of life manual availability	No need of specific recycling operations
Take-back	No

Image of product / Alternate images

Alternative











