

## HORNS AND BUZZERS

### HMA121 Hootronic Electronic Horn



- Accurately reproduces electro-mechanical horn and bell sounds
- High sound output (up to 121dB @ 1m)
- IP66
- Choice of 5 commonly used electro-mechanical sounds
- Continuously rated and low maintenance

#### SPECIFICATIONS

VOLTAGE	VOLTAGE RANGE	CURRENT	Stage 1 Tone	TONE DESCRIPTION	Stage 2	Stage 3
24Vdc	±25%	375mA	Tone 1	Industrial Hooter	Tone 3	Tone 5
115Vac	±10% 50/60Hz	160mA	Tone 2	Medium Frequency Trumpet Horn	Tone 1	Tone 5
240Vac	±10% 50/60Hz	75mA	Tone 3	High Frequency Trumpet Horn	Tone 1	Tone 5
			Tone 4	Buzzer	Tone 2	Tone 5
			Tone 5	Bell	Tone 1	Tone 2

\* Actual current and sound output will depend on tone selected.

<b>Sound Output*:</b>	121dB @1m at nominal voltage
<b>Sound Frequency:</b>	5 Tones
<b>Protection:</b>	IP66
<b>Temp Rating (°C):</b>	-25 to +55
<b>Rating:</b>	Continuous
<b>Cable Entry:</b>	2 x M20
<b>Construction:</b>	Flame retardant ABS, UV stabilized
<b>Weight:</b>	2.5Kg – dc version 3.0Kg- ac version

#### ORDER CODE

<b>ESS8210</b>	HMA121 24Vdc
<b>ESS8220</b>	HMA121 115Vac
<b>ESS8230</b>	HMA121 240Vac

