



APC Service Bypass Panel- 230V; 32A; MBB; Hardwire input; (4) IEC-320 C19 Output

SBP6KRMI2U

#### Overview

Lead time Usually in Stock

#### Main

Main Input Voltage	230 V
Product or component type	Bypass kit
Main Output Voltage	230 V
Number of rack unit	2U
Provided equipment	Installation guide Rack mounting brackets User manual
Range of product	Maintenance Bypass Panels

# **Physical**

Colour	Black
Height	8.9 cm
Width	43.2 cm
Depth	66 cm
Net weight	11.36 kg
Mounting location	Front
Mounting preference	Lower
Mounting mode	Rack-mounted

#### Input

Network frequency	50/60 Hz	
Number of input connectors	1 hard wire 3-wire (1P + N + E)	
Max line current	32 A	
Input current limits	32 A	
Load capacity	7680 VA	
Power factor	01	

# **Output**

Max current draw	32 A
Number of power socket outlets	4 IEC 60320 C10

Protection type	Circuit breaker	
Efficiency	99 %	

## Conformance

Product certifications	CSA GOST
Standards	EN/IEC 62040-1:2019/A11:2021 EN/IEC 62040-2:2006/AC:2006
	EN/IEC 62040-2:2018

## **Environmental**

Ambient air temperature for operation	-2050 °C
Relative humidity	095 %
Operating altitude	015000 ft
Ambient air temperature for storage	-4065 °C
Storage Relative Humidity	095 %
Storage altitude	0.00000000015240.000000000 m

# **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	20.3 cm
Package 1 Width	99.1 cm
Package 1 Length	61 cm
Package 1 Weight	22.72 kg

# **Contractual warranty**

Warranty 2 years (parts only)



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

#### **Use Better**

Materials and Substances	
EU RoHS Directive	Compliant with Exemptions
REACh Regulation	REACh Declaration
Use Again	

#### Use Again

○ Repack and remanufacture	
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
Take-back	No