

Product datasheet

Specifications



APC Smart-UPS X-Series External Battery Pack Rack/Tower 120V, 1200VAh, rackmount, 4U

SMX120BP

Overview

Lead time	Usually Ships within 2 Weeks
-----------	------------------------------

Main

Product or component type	Battery
Number of rack unit	4U
Battery type	Lead-acid battery
Provided equipment	Installation guide Rack mounting brackets
Range of product	Smart-UPS Battery Systems

Batteries & Runtime

Number of battery blocks per string	10
Device mounting	Enclosed battery cartridge
Number of battery filled slots	0
Number of battery free slots	0
Number of battery replacement quantity	2
Battery voltage	120 V
Replacement battery	APCRBC143

Physical

Colour	Black
Height	43.2 cm
Width	17.8 cm
Depth	48.3 cm
Net weight	60.91 kg
Mounting mode	Rack-mounted

Environmental

Ambient air temperature for operation	0...40 °C
Relative humidity	0...95 %
Operating altitude	0...10000 ft
Ambient air temperature for storage	-15...45 °C

Storage Relative Humidity	0...95 %
Storage altitude	0.0000000000...15240.0000000000 m

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	33 cm
Package 1 Width	58.6 cm
Package 1 Length	63.3 cm
Package 1 Weight	65.45 kg

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Carbon footprint (kg.eq.CO2 per CR, Total Life cycle) **300**

Environmental Disclosure [Product Environmental Profile](#)

Use Better

Materials and Substances

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

REACH Regulation [REACH Declaration](#)

Use Again

Repack and remanufacture

Circularity Profile [End of Life Information](#)

Removable battery User replaceable

Take-back Yes