Catalogue No: CAT7N-5.5P-24VAC

STARTER DOL 5.5kW START/STOP 24V AC CONTROL NO OVERLOAD

Motor Control and Drives > Motor Starting and Protection > Assembled Motor Starters > Sprecher + Schuh Motor Starters > Direct On Line (DOL) Motor Starters > CAT7N DOL Starters 5.5 to 18.5kW





Direct On-Line Starter 5.5KW, IP66 Polycarbonate Enclosure, Controlvoltage 24 V AC, Start, Stop Pushbuttons, No Overload

- IP66 ABS V0 insulated enclosure for high ingress protection
- Complete with choice of stop, start and reset pushbuttons to match your application requirements
- 5.5 to 7.5kW: choice of CT7N thermal overload or CEP7 electronic overload (ordered separately)
- 11 to 18.5kW: wide current setting range (5:1) from included CEP7 electronic overload for convenience and flexibility

Representative Photo Only (actual product may vary based on configuration selections)

| SPECIFICATIONS | | |
|---|--|--|
| Product Series | | Streamline Enclosed Motor Starters |
| kW Rating, AC-3, 415V | | 5.5 kW @415V |
| Component Type Motor Control and Drives | | DOL Starter |
| Details, Contactor | | CA7-12 |
| Motor FLC, Min | | 0.1 A, min |
| Motor FLC, Max | | 12.5 A, max |
| IP Rating | | IP66 |
| Motor Connection | | 3 wire |
| Enclosure Type | | Insulated polycarbonate enclosed (IP 66) |
| Control Voltage, AC, Nom | | 24 V AC |
| Button Arrangement | | Start / Stop |
| REFERENCES | | |
| IECEx Certificate - | | |
| Supplier Declaration of Conformity: | | |
| Installation Guide: - | | |
| User Manual: - | | |
| Manufacturer Datasheet: - | | |
| Manufacturer Catalogue & Product Selection: | | |
| | | |



Catalogue No: CAT7N-5.5P-24VAC

STARTER DOL 5.5kW START/STOP 24V AC CONTROL NO OVERLOAD

 $Motor\ Control\ and\ Drives > Motor\ Starting\ and\ Protection > Assembled\ Motor\ Starters > Sprecher\ +\ Schuh\ Motor\ Starters > Direct\ On\ Line\ (DOL)\ Motor\ Starters > CAT7N\ DOL\ Starters\ 5.5\ to\ 18.5kW$



Catalogue No: CAT7N-5.5P-24VAC

STARTER DOL 5.5kW START/STOP 24V AC CONTROL NO OVERLOAD

Motor Control and Drives > Motor Starting and Protection > Assembled Motor Starters > Sprecher + Schuh Motor Starters > Direct On Line (DOL) Motor Starters > CAT7N DOL Starters 5.5 to 18.5kW





