

PASSIVE

MULTISWITCH - END OF LINE

MULTISWITCH 2 WIRE 8 OUTPUTS SATELLITE IF

Product Code: MS2X8

FOXTEL: F30941



- For 8 subscribers or 4 IQ subscribers
- Remote powered by satellite receiver
- The IF polarity selection is controlled by the remote voltage provided by the receiver:
 - < 14.5 V = Vertical
 - > 15.5 V = Horizontal

Specifications	MS2X8
Inputs	2
Outputs / Subscribers	8
Through Loss: SAT-IF: 950 ... 2150 MHz	- 2 ... + 1 dB
Isolation: Input	≥ 24 dB [Typ. 26 dB]
Isolation: Switching	≥ 24 dB [Typ. 26 dB]
Current Consumption	< 70 mA
Capacity (IF Ports) Max	500 mA
Ambient Temperature	- 20 ... + 50 °C
Dimensions (W x D x H mm)	118 x 72 x 19 mm