

Data Sheet

Wireless Door Chime

CAT NO. D642/01, D642/05, D642/012R



D642/01



D642/05



D642/012R

Cat No	D642/01	D642/05	D642/012R
Description	Wireless Door Chime		
Power supply	Battery operated		
Range	Up to 50m		
Sound level	80dB		
Light	Flashing LED light		
Chime	16 melodies		
Colour	White		
Transmitter operating voltage	12 V		
Battery for transmitter	1x A23 12V		
Battery For Receiver	2 x AA 1.5V (not included)	3 x AA 1.5V (not included)	2 x AA 1.5V (not included)
Receiver operating voltage	3Vd.c	4.5Vdc	3Vd.c
Transmission frequency	433.05MHz – 434.79MHz		

Wireless Door Chime

CAT NO. **D642/01, D642/05, D642/012R**



- Wireless battery-operated door chime
- 50 metre operating range
- Flashing light for the hearing impaired
- Vast choice of 16 melodies
- Practical name tag insert
- Slimline and portable design
- Easy to install – no wires or cables
- No signal interference for neighbours
- Can be used as door bell or panic switch
- Each chime and bell press are factory set pairs and are not interchangeable with other HPM door chimes or bell presses
- 3 year warranty

Single product			
Cat No	Dimensions	Weight	Barcode
D642/01	182W x 251H x 32D mm	0.17kg	9321001259053
D642/05	196W x 160H x 30D mm	0.175kg	9321001259299
D642/012R	243W x 172H x 26D mm	0.125kg	9321001434757

Inner box (Qty 4)			
Cat No	Dimensions	Weight	Barcode
D642/01	250W x 180H x 78D mm	0.6kg	9321001374381
D642/05	330W x 165H x 75D mm	0.7kg	9321001374374
D642/012R	405W x 185H x 180D mm	1.25kg	9321001434764

Outer box (Qty 48)			
Cat No	Dimensions	Weight	Barcode
D642/01	577W x 265H x 260D mm	8.22kg	9321001259084
D642/05	600W x 353H x 410D mm	8.72kg	9321001259312
D642/012R	587W x 420H x 398D mm	12.5kg	9321001434771

HPM Legrand - AUS
1300 369 777
www.hpm.com.au
ABN 31 000 102 661

HPM Legrand - NZ
0800 476 009
www.hpm.co.nz

Refer to your group buying office, HPM Legrand Sales Representative or HPM Legrand Sales Office for pricing.

Please note: specifications are subject to change without prior notice.