



ARGO-1200-SEN

CLEVERTRONICS 240V ARGO LED WEATHERPROOF BATTEN WITH MICROWAVE SENSOR AND SWITCHABLE COLOUR



PRODUCT INFORMATION

Part Number	ARGO-1200-SEN
MIC	AUB04620370001
Description	240V ARGO 1200mm LED Weatherproof Batten with Microwave Sensor (Hi/Lo) and Switchable Colour
Construction	Polycarbonate Base and Diffuser with Captive Stainless-Steel Clips (SS301)
Mounting	Surface mount
Dimensions L x W x H	1265mm x 121mm x 88mm
Weight	2.4 kg
Diffuser	Polycarbonate
Driver / Ballast	LED Driver – Merrytek MLC65C P8 (650mA) Important: The Lamp current is factory set any attempt to alter this will result in the warranty being void.
Lamp(s)	Dual LED strip module, 3,000K warm white, 5,700K cool white, 50,000h life [L70/B50 Ta 40°C], Ra>80
Operating Voltage	240V AC; 50Hz
Power Factor	0.85
Supply Current	180mA +/- 20mA
Inrush Current (Max)	15.909A, 160µs
Earth Leakage	0.037-0.047mA
Total lumen output	4202lm (122lm/W @4000K), details see table below
Power Consumption	see table below
IP Rating	IP65
Operating Temperature	0°C to 40°C
Impact Rating	IK08
Alternate Part Number	F4WB-MS-HL
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS60598.1
Compliance Marking (RCM)	

REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1330079	LED HL Driver - MLC65C-P8

Colour	Power Consumption at 650mA setting		Total Lumen Output at 650mA
	Standby Lamp ON	Standby Lamp ON MIN @ 10%	
3000K	37 W	6 W	3673 lm
4000K	35 W	6 W	4202 lm
5700K	37 W	6 W	3970 lm

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order