



### Quick Overview

Smart Bluetooth Downlight Remote Driver (Recessed mount)

### Features

#### Features & Benefits

- Aluminium housing & polycarbonate diffuser
- TUYA App for colour change & dimming control
- Controlled individually or as a group
- Constant current remote driver
- High efficiency SMD chips
- Compatible with Amazon Alexa & Google Max
- IC-4
- 1.0m flex and plug 2-pin
- Operating temp: -20°C to +45°C
- IP44 rated

#### Dimming Options

- Via the TUYA app

### Details

Part No.	TSAL8APDLRGGBT
Brand	ALCHEMY
Unit Of Measure	Each
Voltage AC	200-240V

Proudly Distributed By



1300 555 586

[www.repelec.com.au](http://www.repelec.com.au)

Sign up or log in to [repelec.com.au](http://repelec.com.au)

[f](#) [@](#) [X](#) [v](#) @RepelecAU

<b>Watt</b>	13W
<b>Power Factor</b>	0.9
<b>CCT</b>	2000K-4000K-6500K-RGB
<b>Ra</b>	80
<b>Lifetime (hrs)</b>	50,000
<b>Lumens</b>	780-900-950
<b>Beam Angle</b>	100°
<b>Fitting Colour</b>	White
<b>Dimensions (H x W x øD) mm</b>	38 x 70 x 108
<b>Cutout ømm</b>	90-92
<b>Operating Temperature</b>	-20°C to +45°C
<b>Ingress Protection Rating</b>	IP44