

Catalogue No: **KTA5-32A-C16**

MOTOR PROTECTION CIRCUIT BREAKER KT5 10-16A

Motor Control and Drives > Motor Starting and Protection > Motor Protection Circuit Breakers > Sprecher + Schuh Motor Protection Circuit Breakers > KTA5 Motor Protection Circuit Breakers > KTA5 Motor Protection Circuit Breakers



Motor Protection Circuit Breaker 10...16 Amp



Basic short circuit and thermal protection all-in-one device

- Suitable for three-phase and thermal protection all-in-one device
- Front mount auxiliary contacts require no additional panel space
- Manual motor starting permits on / off motor control for non-severe duty
- Available in a wide range of motor sizes to suit your installation type
- Can be used in variety of control schemes that reduce panel space. Simplify installation and eliminate the need for more expensive equipment
- Wide range of accessories for application flexibility

Representative Photo Only
(actual product may vary based on configuration selections)

SPECIFICATIONS

Component Type Motor Control and Drives	Motor Protection Circuit Breaker
Approx. kW (AC 3, 400/415 V AC)	7.5 kW
kW Rating, AC-3, 415V	7.5 kW @415V
Ie, Rated Operational Current, nom	16 A,nom
Ir, Thermal Trip Setting, Min	10 A min
Ir, Thermal Trip Setting, Max	16 A max
Im, Magnetic Trip Current	240 A
Icu, Rated Ultimate Short-Circuit Breaking Capacity, 400V AC	15 kA @400VAC
Icu, Rated Ultimate Short-Circuit Breaking Capacity, 415V AC	15 kA @415VAC
Ics, Rated Service Short-Circuit Breaking Capacity, 400V AC	10 kA
Ics, Rated Service Short-Circuit Breaking Capacity, 415V AC	10 kA @415VAC

REFERENCES

IECEX Certificate	-
Supplier Declaration of Conformity:	-
Installation Guide:	-
User Manual:	-
Manufacturer Datasheet:	-
Manufacturer Catalogue & Product Selection:	-