Disclaimer. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



APC Smart-UPS SRT 96V 3kVA RM Battery Pack



SRT96RMBP

Overview

Lead time Usually in Stock

Main

Product or component type	Battery	
Number of rack unit	2U	
Battery type	Lead-acid battery	
Provided equipment	Rack mounting brackets User manual Warranty card	
Range of product	Smart-LIPS Rattery Systems	

Batteries & Runtime

Number of battery free slots	0
Number of battery filled slots	0
Battery voltage	96 V
Number of battery replacement quantity	2
Replacement battery	ADCDBC152 [7]

Physical

Colour	Black
Height	8.5 cm
Width	43.2 cm
Depth	59.4 cm
Net weight	40.6 kg
Mounting mode	Rack-mounted

Conformance

Standards OSHPD

Environmental

Ambient air temperature for operation	040 °C
Operating altitude	010000 ft
Relative humidity	0 95 % non-condensing

Ambient air temperature for storage	-1545 °C	
Storage altitude	0.000000000015240.0000000000 m	
Storage Relative Humidity	095 % non-condensing	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	23.900 cm
Package 1 Width	59.900 cm
Package 1 Length	83.100 cm
Package 1 Weight	44.500 kg

Contractual warranty

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

∇ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	204
Environmental Disclosure	Product Environmental Profile

Use Better

EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration
China RoHS Regulation	China RoHS declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable
Take-back	Yes