



APC Smart-UPS On-Line SRT Rackmount Battery Pack for 2.2kVA Extended runtime model 72V

SRT72RMBP

Overview

Lead time Usually in Stock

Main

Product or component type	Battery
Number of rack unit	2U
Battery type	Lead-acid battery
Provided equipment	Documentation CD Installation guide Rack mounting brackets
Range of product	Smart-UPS Battery Systems

Batteries & Runtime

Number of battery free slots	0
Number of battery filled slots	0
Battery voltage	72 V
Number of battery replacement quantity	2
Replacement battery	APCRBC141 ☐

Physical

Colour	Black	
Height	8.5 cm	
Width	43.2 cm	
Depth	59.4 cm	
Net weight	33.9 kg	
Mounting mode	Rack-mounted	

Conformance

Standards OSHPD

Environmental

Ambient air temperature for operation	040 °C
Operating altitude	010000 ft
Relative humidity	095 % non-condensing

Ambient air temperature for storage	-1545 °C
Storage altitude	0.000000000015240.000000000 m
Storage Relative Humidity	0 95 % non-condensing

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	23.900 cm
Package 1 Width	59.900 cm
Package 1 Length	83.100 cm
Package 1 Weight	40.820 kg
Unit Type of Package 2	PAM
Number of Units in Package 2	2
Package 2 Height	100.000 cm
Package 2 Width	100.000 cm
Package 2 Length	120.000 cm
Package 2 Weight	93.640 kg

Contractual warranty

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	187
Environmental Disclosure	Product Environmental Profile

Use Better

EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration
China RoHS Regulation	China RoHS declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable
Take-back	Yes