

# NetShelter SX Air Recirculation Prevention Kit

AR7708

### Overview

Presentation	This kit prevents the recirculation of warm air exhaust inside the enclosure by closing gaps between the vertical mounting flanges and the side panels of the enclosure. The kit includes components for 42U and 48U enclosure heights.

Lead time While Supplies Last

#### **General**

Provided equipment Installation guide

# **Physical**

Colour	Black
Depth	1.9 cm
Height	213.4 cm
Net weight	0.25 kg
Width	1.9 cm

# **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	10.8 cm
Package 1 Width	52.7 cm
Package 1 Length	24.5 cm
Package 1 Weight	0.58 kg

## **Contractual warranty**

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

#### **Use Better**

Materials and Substances	
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration

#### **Use Again**

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Take-back	Yes