# Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications





# APC Replacement Battery Cartridge 33 with 2 Year Warranty

RBC33

### Overview

Lead time Usually in Stock

### Main

Product or component type	Replacement battery cartridge	
Battery type	Lead-acid battery	
Provided equipment	All required connectors  Battery recycling guide  Reusable packaging Installation quide	

## **Batteries & Runtime**

Number of battery blocks per string	2	
Number of battery free slots	0	
Number of battery filled slots	0	
Device mounting	Enclosed battery cabinet	
Battery voltage	24 V	
Number of battery replacement quantity	1	

# **Physical**

Colour	Charcoal
Height	19.7 cm
Width	14.9 cm
Depth	6.4 cm
Net weight	5.33 kg
Mounting mode	Not rack-mountable

# **Output**

Battery capacity 9.0 Ah

# **Environmental**

Ambient air temperature for operation	040 °C
Operating altitude	010000 ft
Relative humidity	095 %

Ambient air temperature for storage	040 °C
Storage altitude	0.00000000003048.0000000000 m
Storage Relative Humidity	0. 95 %

# **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	30.5 cm
Package 1 Width	10.2 cm
Package 1 Length	22.9 cm
Package 1 Weight	5.91 kg

# **Contractual warranty**

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

### Environmental Data explained >

How we assess product sustainability >

∅ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	19
Environmental Disclosure	Product Environmental Profile

### **Use Better**

EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration
China RoHS Regulation	China RoHS declaration

### **Use Again**

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Take-back	Yes