Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

APC



APC Smart-UPS SRT 192V 5kVA and 6kVA RM Battery Pack Marine

SRT192RMBPM

Overview

Lead time Usually in Stock

Main

Product or component type	Battery	
Number of rack unit	3U	
Battery type	Lead-acid battery	
Provided equipment	Installation guide Warranty card	

Batteries & Runtime

Device mounting	Stand alone battery stack	
Number of battery filled slots	0	
Number of battery free slots	0	
Number of battery replacement quantity	2	
Battery voltage	192 V	
Replacement battery	APCRBC140 ☐	

Physical

Colour	Black
Height	13 cm
Width	43.2 cm
Depth	68.27 cm
Net weight	91 kg
Mounting mode	Rack-mounted

Environmental

Ambient air temperature for operation	040 °C	
Relative humidity	095 % non-condensing	
Operating altitude	010000 ft	
Ambient air temperature for storage	-1545 °C	
Storage Relative Humidity	095 % non-condensing	
Storage altitude	0.000000000015240.000000000 m	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	42 cm
Package 1 Width	100 cm
Package 1 Length	60 cm
Package 1 Weight	105.5 kg

Contractual warranty

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	483
Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances	
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration
☼ Energy efficiency	
Optimized Energy Efficiency	Energy efficient product

Use Again

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable
Take-back	Yes