



APC Easy UPS Lithium-ion External Battery Pack for 6kVA SRVL Extended runtime model, 48V 4800Wh, 3U Rackmount

SRVL48RMBP3U

## **Overview**

Presentation	Double-conversion On-line UPS with Lithium-Ion battery to scalable runtime. Ideal UPS for essential power protection needs even in the most unstable power conditions.
Lead time	Usually in Stock

### Main

Product or component type	Battery
Number of rack unit	3U
Battery type	Li-lon (Lithium-lon)
Provided equipment	RJ11 cable Power cable Rack mounting brackets User manual
Range of product	Safety guide  Easy UPS On-Line

## **Batteries & Runtime**

Number of battery filled slots	0
Number of battery free slots	0
Battery voltage	48 V

# **Physical**

Colour	Black with silver front bezel
Height	13.1 cm
Width	43.8 cm
Depth	61.6 cm
Net weight	49.5 kg
Mounting mode	Rack-mounted

# **Conformance**

Product certifications	CE	
	UKCA	
	UN 38.3	
	IEC 62619	

## **Environmental**

Ambient air temperature for	050 °C
operation	

Relative humidity	095 % non-condensing	
Operating altitude	03000 m	
Ambient air temperature for storage	-2060 °C	
Storage Relative Humidity	095 % non-condensing	
Storage altitude	015000 m	

# **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	41.2 cm
Package 1 Width	60 cm
Package 1 Length	80 cm
Package 1 Weight	64.3 kg

# **Contractual warranty**

Warranty 5 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability

# ∅ Environmental footprint

Environmental Disclosure

Product Environmental Profile

#### **Use Better**

#### 

EU RoHS Directive Compliant with Exemptions

REACh Regulation REACh Declaration

### **Use Again**

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable
Take-back	No